

BRUSHLESS MOTORS
NX860EAJ
ELECTRONIC DRIVE (1)
DIGIVEX 30/60 et DIGIVEX 32/64
(230 V) (400 V)




Torque at low speed	M_o	Nm	41
Permanent current at low speed	I_o	A_{rms}	18.6
Peak torque	M_p	Nm	137
Current for the peak torque	I_p	A_{rms}	74
Back emf constant at 1000 rpm (25°C)*	K_e	V_{rms}	138
Torque sensitivity	K_t	Nm/A_{rms}	2.21
Winding resistance (25°C)*	R_b	Ω	0.499
Winding inductance*	L	mH	6.43
Rotor inertia	J	$kgm^2 \times 10^{-5}$	920
Thermal time constant	T_{th}	min	60
Motor mass	M	kg	27
Voltage of the mains	UR1 UR2 UR3	V_{rms}	230 400 480
Rated speed	Nn1 Nn2 Nn3	rpm	1450 2600 3000
Rated torque	Mn1 Mn2 Mn3	Nm	35.58 27.47 23.85
Rated current	In1 In2 In3	A_{rms}	16.28 12.78 11.22
Rated power	Pn1 Pn2 Pn3	W	5400 7480 7490

All data are given in typical values under standard conditions

* Phase to phase

(1) Please check the availability of this drive with 480 V

Voltages and currents are given in rms values



Characteristics are given for an optimal drive of the motor

FICHE-009

Création: 06 juin 2002	Edition: 10/févr/2005	NX860EAJ	.b
------------------------	-----------------------	----------	----